

16

# TOPICS - (Network Configuration in Silent Mode or without GUI) Netca Response File

```
# cd /opt/database/response
```

```
# ls -l
```

```
# cp netca.rsp /u01/app/oracle/netca/oracle.rsp
```

→ name of server

```
# cd /u01/app/oracle
```

39

```
# vi netca-oracle.rsp
```

```
Show GUI = false
```

→ make this directory

```
LOG_FILE = "/u01/app/oracle/product/11.2.0/dbhome_1/  
network/tools/log/netcablog"
```

! wo

```
# export ORACLE_BASE = /u01/app/oracle
```

```
# export ORACLE_HOME = /u01/app/oracle/product/11.2.0/  
dbhome_1
```

```
# export PATH = $PATH : $ORACLE_HOME/bin
```

```
# echo $ORACLE_BASE
```

```
# echo $ORACLE_HOME
```

```
# echo $PATH
```

```
# which netca
```

```
# netca -silent -responseFile /u01/app/oracle/netca/  
oracle.rsp
```

- profile configuration complete

exitcode 0 ✓

```
# lsnetctl status
```